



## FIREYE MARKETING MEMO #111910/JD

November 19, 2010

---

BurnerLogix Flame safeguards used in SIL 2 Safety Applications

**Background Fireeye Controls and Safety Testing** - A critical part of certifications and agency testing (TUV, DVGW, DIN, CE) is extensive analysis to verify that the products are fail-safe as defined in clause 9 (Protection against internal faults) of EN298.

EN 298, clause 9 states the system shall be fail-safe. It further defines that the system must be fail-safe with any 2 concurrent hardware and/or software faults. Verifying that capability required several months of detailed failure mode testing and analysis, involving design engineers and test technicians. The general procedure is as follows:

(1) One by one, a fault is asserted in every component and software module in the product. With that fault asserted, the product must immediately either a) de-energize the flame relay or b) continue to operate in compliance with all applicable standards.

(2) If, in response to the fault asserted in (1) above, the product responds as described in b) above, then, one by one, while maintaining the first fault, a second fault must be asserted in every component and software module in the product. With two faults now asserted, the product must immediately either a) de-energize the flame relay or b) continue to operate in compliance with all applicable standards.

The Fireeye control listed passed rigorous test and analysis and each has been certified by TUV (arguably the most demanding agency in the world) as meeting the requirements of EN298.

**MTBF and use with SIL classifications -**

**MTBF, Failure Mode Analysis, SIL calculation information**

In order to make a SIL calculation for probability of failure on demand average (PFDavg), we need to specify the dangerous failure rate of the product. The dangerous failure rate of the products are the failure rate of the times that they will see or indicate flame when there is not flame, i.e. fail to trip on loss or lack of flame. Total numbers can be used but two other parameters are required. First is the percent safe failures and the second is the dangerous diagnostic coverage (that percent of the scanner's diagnostics that will detect dangerous failures from the over all dangerous failure modes). With regard to installation, it is assumed for these calculations that the installation is completed correctly and tested at startup to insure the proper installation. These numbers do not allow for any other systems or controls that may be connected to the Fireeye products only for the operation of the Fireeye products themselves.



**BurnerLogix Series family Numbers**

Failure rate (note this is based on the MTBF years of the various components that make up the product and assumes a conservative analysis) = 0.031 failure per year = 3.54E-06 per hour  
MTBF (dem) = 1/failure rate = 32.25 years

- Overall failure rate = 3.54E-06 per hour
- Assumed Safe failure % = 50%
- Safe Failure Rate = 1.77E-06
- Dangerous failure rate w/o diagnostics = 1.77E-06
- Dangerous Diagnostic Coverage = 98.7%
- Dangerous failure rate w/ diagnostics = 2.30E-08

Probability of failure on demand can be calculated from the above. The calculation used is

$$PFD_{avg} \sim \frac{1}{2} \lambda_u T_i = \frac{T_i}{2 \times MTBF_{FTD}}$$

- PFD<sub>avg</sub> = Average Probability Failure on Demand,
- λ<sub>u</sub> = Unrevealed Failure Rate (per year),
- T<sub>i</sub> = Test interval in years between the life testing of the protective function,
- MTBF(FTD) = Mean Time Between Failure (Fail To Danger) [yr]

The unknown is the T<sub>i</sub> - This would typically be defined by the customer's specific needs or to meet a particular safety level. In general the more frequent the test interval the better the PFD and therefore the higher the SIL level that can be accommodated with the product

Using the calculations above and assuming (T<sub>i</sub> @ 2 years) the product has a PFD of 2.015 x 10<sup>-4</sup>. This would mean the product would exceed the requirements for use in a SIL 2 category.

Regards

John Devine  
**Vice President Sales and Marketing**  
Fireeye Inc.